

UDC1200 & UDC1700 Universal Digital Controllers Series Micro-Pro Specifications

51-52-03-35 June 2011



Overview

The UDC1200 & UDC1700 are microprocessor-based 1/16 DIN and 1/8 DIN controllers, which combine a high degree of functionality and reliability at low cost.

They are fully dedicated to monitor and control temperatures, pressures and levels in a wide range of applications such as environmental chambers, furnaces, ovens, packaging machines and other applications in plastics and the food and beverage industries. The large and easy-to-read dual 4-digit display and tactile keypad make the UDC1200 and UDC1700 easy to configure and use. Their outstanding flexibility enables you to configure any unit for any application and change it if required.

For the thousands of satisfied UDC1000/1500 users, the UDC1200/ 1700 controllers are downward compatible to existing UDC1000/1500 applications and installations.

Features

Dual display

Two 4-digit displays with 7 LED segments, each configurable for:

- PV and SP (non adjustable)
- PV and SP (adjustable)
- PV and Ramping SP
- PV only

Easier to configure

Two different configuration levels (Configuration mode and set-up mode) provide easy access to parameters. A 4-digit security code prevents unauthorized changes.

Moisture resistant front-face

Meets NEMA 3 / IP65 front-face protection against dust and water.



UDC1700



UDC1200

Universal input

Accept seven different types of thermocouples, RTDs, current and voltage linear inputs. All inputs are configurable as standard.

Universal power supply

The UDC1200 and UDC1700 can operate on any line voltage from 90 Vac to 264 Vac at 50/60 Hz. A 24/48 Vac/dc model is available as an option.

Easy upgrade

All the option boards are jumper free and detected automatically by the instrument.

Easy output selection

All the outputs (including the control output) of the instrument can be changed to meet the exact customer's needs.

Alarm strategy

Two soft alarms for PV, deviation high/low/absolute. A special loop alarm is also provided to detect faults in the control loop by continuously analyzing the PV response to the control output. Alarm inhibit is available on power up and setpoint switching.

Manual/Automatic mode

Manual control (via bumpless transfer) is enabled by simply pressing the front-face AUTO/MAN key. The "SET" LED flashes and the output power is displayed on the lower display. Output can be adjusted with the upper and lower keys.

Pre-tuning and self-tuning strategy

Pre-tuning is used to set up the PID parameters close to the optimum values, which the self-tuning algorithm uses to subsequently optimize the tuning parameters.

Limit controller

Packaged in 1/16 DIN, the UDC1200 limit controller is designed to provide a safety shut-off and optional alarm for use in a wide variety of applications.

Up to three outputs

The UDC1200 and UDC1700 provide up to three outputs for time and current proportioning, duplex mode (heat/cool), PV or SP retransmission, and alarms.

Setpoint ramp

The current setpoint can ramp to a new-targeted setpoint by way of a user defined ramp rate.

Dual setpoint

Dual setpoint option is available on the UDC1200 and UDC1700. The current setpoint is selected by a digital input. This option is exclusive with UDC1200 limit model remote alarm reset.

Communication

An optional RS485 communications interface is available on the UDC1200 and UDC1700. It provides a link for up to 32 units and a host computer through ASCII or Modbus RTU protocol at up to 19200 baud.

Highly secure

A non-volatile memory based on EEPROM technology ensures data integrity during loss of power supply, with retention of more than 100 years. A 4-digit security code prevents unauthorized or accidental change.



UDC1700

Upper display: 4 characters dedicated to show the PV. In configuration mode, it shows the parameter value or selection

Lower display: 4 characters dedicated in normal operation mode to display the SP. In configuration mode, it displays the parameter name.



UDC1200



Selects manual or automatic mode. Becomes « Reset » on UDC1200 Limit model.



Allows operator mode parameters to be scrolled. In combination with the «Upper» key, allows configuration mode or Setup mode to be entered.



Increases setpoint, output or configuration parameter values.



Decreases setpoint, output or configuration parameter values.

Optional Features

The following can be selected via the Model selection Guide (see page 8):

- RS485 ASCII communication
- RS485 Modbus RTU communication
- Digital Input
- Output 2
- Output 3
- Power Supply 24/48 Vac/dc

Physical Description

The UDC1200 controller is housed in a 110 mm (4.33 inches) deep case with a standard UDC gray bezel. It can be mounted in a 1/16 DIN panel cutout.

The UDC1700 controller is housed in a 100 mm (3.94 inches) deep case and can be mounted in a 1/8 DIN panel cutout. By using the pre-assembled mounting fixture delivered with the unit, you can easily and securely install the controller into the panel cutout. Modular plug-in construction allows rapid access and saves time. All inputs and outputs are connected on the rear terminal block by screws.

Operator Interface

Four display combinations are offered to the operator. The upper 4-digit 7-segment display is always dedicated to monitor the PV. The lower display can show:

- SETPOINT (read only)
- SETPOINT (adjustable)
- RAMPING setpoint (ramp mode)
- BLANK

Universal Inputs

All input types are available on any unit. Selection among the various types of inputs is made by prompt configuration. As soon as the Process Variable reaches the value of the input range limit, the controller displays a message. A sensor break indication is also provided. A configurable digital filter is available from 0.5 seconds to 100.0 seconds.

Outputs

Three types of outputs (RELAY, SSR driver or DC linear) are selectable for three outputs, through the model selection guide or by adding a plug-in module for outputs 1, 2 and 3.

Outputs Algorithm

The UDC1200 and UDC1700 are available with the following output algorithms:

- *Time proportional:*
ON/OFF or time proportional with electromechanical relay SPDT 2 A or SSR driver (open collector).
- *Current proportional:*
Supply directly proportional current or voltage signal to the final control elements which require 0-20 mA, 4-20 mA, 0-10 V or 0-5 V.
- *Time proportional duplex:*
Three duplex modes can be selected, either ON/OFF duplex, time proportional duplex (heat/cool with two proportional bands, two cycle times and deadband) or TPSC.
- *Current proportional duplex:*
In addition to the first current/voltage output, a second similar output with its own proportional band is provided.
- *Current/Time or Time/Current duplex:*
Provides a variation of traditional time or current duplex mode by mixing current and time proportioning together.

Control Algorithms

Four control algorithms can be set up through the configuration menu:

- On/Off
- PID
- PD + MR
- TPSC

The TPSC (Three Position Step Control) control algorithm is dedicated to control valve positioning without slidewire feedback from the motor shaft.

Configuration

There are two levels of configuration. The SET-UP mode allows modification of current parameters such as tuning parameters, alarm values, setpoint limit, ramp enable, auto-manual mode enable and auto-pretune enable.

The CONFIGURATION mode is more oriented to unit personality: input selection, output 2 and 3 usage, alarm type, communication address and lockout code.

The operator mode screens are only selectable via the configuration software only. For instance, the alarm value screen can be moved from setup mode to normal operator mode if desired.

Control Mode

Manual or automatic mode with bumpless transfer is standard feature. In manual mode, the operator can directly control the output through the two front face keys (raise and lower keys). The output value is monitored on the lower display.

Alarms

Outputs 1, 2 and 3 can be used as alarms. Two electromechanical single pole double throw relays can activate external equipment when alarm setpoints are reached. An LED is also activated on the front-face. A direct or reverse acting alarm output can be configured. A logical combination of the two alarms: OR, AND or hysteresis (active when both alarms are active and inactive when both alarms are inactive) can be set which associates the two alarms status before energizing the relay. In order to detect a defective control loop, the controller can supply special loop alarm control by continually monitoring the PV response to output demand. A timer is automatically set up when any output is on saturation mode. When the timer reaches twice the reset time with no PV response, the loop alarm is activated. With this soft alarm there is no need for a heater circuit breaker, saving wiring time and costs.

Display

Dual, four-digit LED display with decimal point location configurable up to three places for linear ranges only.

Limit Controller

The UDC1200 1/16 DIN limit controller provides a latched relay output which is activated when the process parameters either exceed or fall below the desired value, providing a failsafe cut-off which has to be manually reset before the process can continue.

The UDC1200 limit controller can be configured to be either a "high limit" unit where the delay will de-energize when the PV is above the limit setpoint, or a "low limit", where the relay will drop out when the PV falls below the setpoint.

A LED indicator shows when limits have been exceeded, and when the relay is latched out.

The optional digital input allows a remote reset function.

Remote Setpoint Model

The UDC1700 1/8 DIN "R" model controller has a second input available that accepts either a linear or potentiometer input signal as a remote setpoint. The input signals accepted are field-configurable and are: 0-5 V, 1-5 V, 0-10 V, 2-10 V, 0-20 mA, 4-20 mA (factory set), 0-50 mV, 10-50 mV, 0 100 mV, or 0-2000 ohms. This allows the controller to act as a "slave" controller accepting a setpoint value from a 'master' device such as a PLC or setpoint-programming controller (such as the DCP50, DCP100, DCP300, or DCP550 series).

The UDC1700R also includes a standard digital input allowing remote switching between the local setpoint and the remote setpoint value. Also standard in this model is "fuzzy" autotune software that minimizes process variable overshoot when responding to a setpoint change.

PC Software

The UDC1200 & 1700 are supported with PC software allowing you to quickly configure your device using configuration wizards, or to perform diagnostics.

Specifications (Applies to both UDC1200 and UDC1700)

Technical data	
Accuracy	0.1 % of span $\pm$ 1 LSD
Temperature Stability	0.01 % of span per °C
Input Signal Failure	<i>Fail-safe output value:</i> Achieved when burnout is detected. Value depends on configuration. <i>For thermocouple and mV input detected by any lead break:</i> Upscale burnout <i>For RTD:</i> Burnout detected by any lead break <i>Current or voltage input:</i> Burnout set by open circuit detection
Input Impedance	<i>Voltage impedance:</i> 47 Kohms <i>Current input:</i> 4.7 ohms <i>All others:</i> 100 Mohms
Input Sampling Rate	Four samples per second
Input Filter	Digital filter configurable from front panel 0.0 (Off), from 0.5 seconds to 100.0 seconds in 0.5 seconds increment
Input Resolution	14 bits approximately, always four times better than display resolution
Input Isolation	Universal input isolated at 2500 V from all outputs except SSR and from power supply
Stray Rejection	<i>Common mode rejection:</i> > 120 dB at 50/60 Hz <i>Serial mode rejection:</i> > 500% of span at 50/60 Hz
Approvals	UL recognized to US & Canadian standards FM approval on the UDC1200 limit model Product design to meet CE MARK requirement
Control Output Type	Type available: <i>Output 1/2/3:</i> DC, Electromechanical relay, SSR drive (open collector) DC linear output: 0-20 mA, 4-20 mA, 0-5 V, 0-10 V <i>Accuracy:</i> $\pm$ 0.25 % (250 ohms for mA, 2 Kohms for voltage) <i>Resolution:</i> 80 bits in 250 ms (10 bits in 1 second typical > 10 bits in > 1 second) <i>Load impedance:</i> 500 ohms maximum for current output, 500 ohms minimum for voltage output <i>Isolation:</i> Isolated 2500 V from all other inputs and outputs <i>Range selection method:</i> Front panel code setting <i>Temperature stability:</i> 0.01 % / °C <i>Electromechanical relay:</i> SPDT contact <i>Resistive load:</i> 2 A at 120 V or 240 V <i>Life time:</i> > 500000 operations at rated voltage/current SSR drive/TTL: <i>Drive capability:</i> SSR > 10 Vdc into 250 ohms minimum <i>Isolation:</i> Not isolated from input and other SSR output
Alarms	<i>Maximum number of alarms:</i> 2 soft alarms setpoint + 1 loop alarm Alarm inhibit available on power up and setpoint switching <i>Alarm output:</i> Up to two relays or SSR output on outputs 2 and 3 <i>Types:</i> PV high or low, band, deviation high or low, loop <i>Combination alarms:</i> Logical "OR", "AND" or hysteresis of alarms available to individual hardware output

Loop Control	<i>Automatic tuning type:</i> Pre-tune and self-tune <i>Proportional bands:</i> 0 (inactive), 0.5 % to 999.9 % of input span with 0.1% increments. Two proportional bands available for duplex mode <i>Reset:</i> Off or from 1sec. to 99 min 59 sec. <i>Rate:</i> From 0 sec. to 99 min 59 sec. <i>Manual reset:</i> from 0 to 100 % of output (single output), from –100 % to 100 % of output (dual output) <i>Deadband:</i> ± 20 of PB1 + PB2 <i>ON/OFF hysteresis:</i> 0.1% to 10.0 % of input span <i>Auto/manual mode:</i> Front key selectable with bumpless transfer between automatic and manual mode <i>Cycle times:</i> Up to two cycle times available for time duplex control <i>Selection:</i> 0.5, 1, 2, 4, 8, 16, 32, 64, 128, 256, or 512 seconds <i>Setpoint ramp:</i> From 1 to 9999 engineering units per hour
Retransmission Output	Any output can be selected to retransmit the process value or setpoint as a linear (current or voltage) output
Digital Input (optional)	On contact the digital input will switch between SP1/SP2 or Auto/Manual or DC100L Remote Reset
Communication Interface	RS485 – ASCII or Modbus RTU (selectable from the menu) <i>Baud rate:</i> 1200, 2400, 4800, 9600 or 19200 baud <i>Link characteristics:</i> 32 drops maximum, ASCII or Modbus protocols, two wires
Mounting	Plug-in with pre-assembled mounting fixture
Wiring Connection	Screw terminals on the rear of the case (combination head)
Power Consumption	4 W
Physical (UDC1200)	<i>Weight:</i> 210 grams maximum <i>Height:</i> 48 mm / 1.89 in <i>Width:</i> 48 mm / 1.89 in <i>Depth:</i> 110 mm / 4.33 in <i>Cut out:</i> 45 mm x 45 mm / 1.77 in x 1.77 in
Physical (UDC1700)	<i>Weight:</i> 250 grams maximum <i>Height:</i> 96 mm / 3.78 in <i>Width:</i> 48 mm / 1.89 in <i>Depth:</i> 100 mm / 3.94 in <i>Cut out:</i> 45 mm x 92 mm / 1.77 in x 3.62 in
Environmental	<i>EMI Susceptibility:</i> Designed to meet EN55101 <i>EMI Emission:</i> Designed to meet EN55022 <i>Safety Considerations:</i> Designed to comply with IEC1010-1as far as applicable
Front Panel Sealing	NEMA 3 / IP66

Input Actuations			
		Ranges	
Thermocouple types		°F	°C
(Fixed decimal)	R	32 – 3198	0 – 1759
	S	32 – 3204	0 – 1762
	J	-328 – 2192	-200 – 1200
	J	-199.9 – 999.9	-128.8 – 537.7
	T	-400 – 752	-250 – 400
	T	-199.9 – 752	-128.8 – 400
	K	-400 – 2503	-240 – 1373
	K	-128.8 – 537.7	-199.9 – 999.9
	L	32 – 1403	0 – 762
	L	32 – 999.9	0 – 537.7
	B	211 – 3315	100 – 1824
	C	32 – 4208	0 – 2320
	N	32 – 2551	0 – 1399
RTD: (3 wires connection)			
PT100 (IEC) $\alpha = 0.00385$			
(Fixed decimal)		-328 – 1472 -199.9 – 999.9	-199 – 800 -128.8 – 537.7
DC linear:		10 – 50 mV 4 – 20 mA 1 – 5 V 2 – 10 V	0 – 50 mV 0 – 20 mA 0 – 5 V 0 – 10 V

Operating Conditions			
	Reference Conditions	Operative Limits	Transportation and Storage
Ambient Temperature	20 °C $\pm$ 2 °C (68 °F $\pm$ 4 °F)	0 °C to 55 °C (32 °F to 131 °F)	-20 °C to 80 °C (-4 °F to 176 °F)
Relative Humidity	60-70 %	20-95 % non -condensing	
Voltage	90-264 Vac $\pm$ 1 %	90-264 Vac	
Frequency	50 Hz	50-60 Hz	
Source Resistance	< 10 ohms for thermocouple	1000 ohms maximum for thermocouple	
Lead resistance for RTD	< 0.1 ohm/lead (PT100)	50 ohms per lead maximum balanced	

Sales and Service

For application assistance, current specifications, pricing, or name of the nearest Authorized Distributor, contact one of the offices below.

Asia Pacific Global Technical Support Field Instruments

Phone: +65 6580 3156
Fax: +65 6445-3033

Australia

Honeywell Limited
Phone: +(61) 7-3846 1255
FAX: +(61) 7-3840 6481
Toll Free 1300-36-39-36
Toll Free Fax: 1300-36-04-70

China – PRC - Beijing

Honeywell China Inc.
Phone: +(86-10) 8458-3280
Fax: +(86-10) 8458-4650

China – PRC - Shanghai

Honeywell China Inc.
Phone: (86-21) 5257-4568
Fax: (86-21) 6237-2826

China – PRC - Chengdu

Honeywell China Inc.
Phone: +(86-28) 6613-5078
Fax: +(86-28) 8678-7061

China – PRC - Xi'an

Honeywell China Ltd - Xi'an.
Phone: +(86-29) 8833-7490
Fax: +(86-29) 8833-7489

China – PRC - Shenzhen-

Honeywell China Inc.
Phone: +(86) 755-2518-1226
Fax: +(86) 755-2518-1221

Indonesia

PT Honeywell Indonesia
Phone: +(62) 21-535-8833
FAX: +(62) 21-5367 1008

Honeywell Automation India Ltd.

Honeywell Ltd.
Phone: +(91) 6603-9400
Fax: +(91) 6603-9600

Japan

Honeywell Inc.
Phone: +(81) 3 6730 7197
Fax: +(81) 3 6730 7228

Malaysia

Honeywell Engineering Sdn Bhd
Phone: +(603) 7958-4788
Fax: +(603) 7958-8922

New Zealand

Honeywell Limited
Phone: +(64-9) 623-5050
Fax: +(64-9) 623-5060
Toll Free (0800) 202-088

Singapore

Honeywell Pte Ltd.
Phone: +(65) 6580 3278
Fax: +(65) 6445-3033

South Korea

Honeywell Korea Co Ltd
Phone: +(822) 799 6114
Fax: +(822) 792 9015

Thailand

Honeywell Systems (Thailand) Ltd.
Phone: +(662) 693-3099
FAX: +(662) 693-3089

Taiwan R.O.C.

Honeywell Taiwan Ltd.
Phone: +(886-2) 2245-1000
FAX: +(886-2) 2245-3243

SE Asia Countries

see Honeywell Pte Ltd (Singapore)
for: Philippines, Pakistan, Cambodia, Guam, Laos, Myanmar, Vietnam, East Timor

SE Asia Countries

see Honeywell Automation India Ltd for: Bangladesh, Nepal, Sri Lanka

EUROPE

Austria

Honeywell Austria GmbH
Phone: +43 (316)400123
FAX: +43 (316)40017

Belgium

Honeywell SA/NV
Phone: +32 (0)2728 24 07
FAX: +32 (0)2728 22 45

Bulgaria

Honeywell EOOD
Phone: +(359) 2 40 20 900
FAX: +(359) 2 40 20 990

Czech Republic

Honeywell spol. s.r.o.
Phone: +420 242 442 232
FAX: +420 242 442 131

Denmark

Honeywell A/S
Phone: +(45) 39 55 55 55
FAX: +(45) 39 55 55 58

Finland

Honeywell OY
Phone: +358 (0)20752 2753
FAX: +358 (0) 20752 2751

France

Honeywell SA
Phone: +33 (0)1 60198075
FAX: +33 (0)1 60198201

Germany

Honeywell AG
Phone: +49 (69)8064-299
FAX: +49 (69)806497336

Hungary

Honeywell Kft.
Phone: +36-1-451 4300
FAX: +36-1-451 4343

Italy

Honeywell S.p.A.
Phone: +390292146307
FAX: +39 0292146377

The Netherlands

Honeywell B.V.
Phone: +31 (0) 20 5656200
FAX: +31 (0) 20 5656210

Norway

Honeywell A/S
Phone: (45) 39 55 55 55

Poland

Honeywell Sp. zo.o
Phone: +48-22-6060900
FAX: +48-22-6060901

Portugal

Honeywell Portugal Lda
Phone: +351 21 424 5000
FAX: +351 21 424 50 99

Romania

Honeywell Bucharest
Phone: +40 (0) 21 2316437
FAX: +40 (0) 21 2316439

Russian Federation (RF),

Honeywell Field Solutions
Kievskaya str., 7,
Moscow 121059, Russia
Phone +7 (495) 796 98 60
Fax +7 (495) 797 99 64

Slovak Republic

Honeywell s.r.o.
Phone: +421-2-58247 410
FAX: +421-2-58247 415

Spain

Honeywell S.A.
Phone: +34 (0)91313 61 00
FAX: +34 (0)91313 61 30

Sweden

Honeywell AB
Phone: +(46) 8 775 55 00
FAX: +(46) 8 775 56 00

Switzerland

Honeywell AG
Phone: +41 18552448
FAX: +(41) 1 855 24 45

Turkey

Honeywell Turkey A.S.
Phone: +90 216 578 71 00
FAX: +90 216 575 66 35

Ukraine

Honeywell
Tel: +380-44-201 44 74
Fax: +380-44-201-44-75

United Kingdom

Honeywell Control Systems Ltd.
Phone: +44 (0)1344 655251
FAX: +44 (0) 1344 655554

MIDDLE EAST

Abu Dhabi U A E

Middle East Headquarters
Honeywell Middle East Ltd.
Phone: +971 2 4041246
FAX: +971 2 4432536

Sultanate of Oman

Honeywell & Co Oman LLC
Phone: +968 24 701153/
Ext.33
FAX +968 24 787351

Saudia Arabia

Honeywell Turki Arabia Ltd
Jubail Office
Phone: +966-3-341-0140
Fax: +966-3-341-0216
Honeywell - ATCO
Dammam Office
Phone: 0096638304584
Fax: 0096638338059

Kuwait

Honeywell Kuwait KSC
Phone: +965 242 1327 to 30
Fax: +965 242 8315
And
Phone: +965 326 2934/1821
Fax: +965 326 1714

AFRICA

Mediterranean & African Distributors

Honeywell SpA
Phone: +39 (02) 250 10 604
FAX: +39 (02) 250 10 659

South Africa (Republic of) and sub saharan

Honeywell Southern Africa
Honeywell S.A. Pty. Ltd.
Phone: +27 11 6958000
FAX +27 118051504

NORTH AMERICA

Canada

Honeywell LTD
Phone: 1-800-737-3360
FAX: 1-800-565-4130

USA

Honeywell Process Solutions,
Phone: 1-800-423-9883
Or 1-800-343-0228
Email: ask-ssc@honeywell.com

SOUTH AMERICA

Argentina

Honeywell S.A.I.C.
Phone: +(54-11) 4383-3637
FAX: +(54-11) 4325-6470

Brazil

Honeywell do Brasil & Cia
Phone: +(55-11) 7266-1900
FAX: +(55-11) 7266-1905

Chile

Honeywell Chile, S.A.
Phone: +(56-2) 233-0688
FAX: +(56-2) 231-6679

Mexico

Honeywell S.A. de C.V.
Phone: +(52) 55 5259-1966
FAX: +(52) 55 5570-2985

Puerto Rico

Honeywell Inc.
Phone: +(809) 792-7075
FAX: +(809) 792-0053

Trinidad

Honeywell Inc.
Phone: +(868) 624-3964
FAX: +(868) 624-3969

Venezuela

Honeywell CA
Phone: +(58-2) 238-0211
FAX: +(58-2) 238-3391

Model Selection Guides are subject to change and are inserted into the specifications as guidance only.
Prior to specifying or ordering a model check for the latest revision Model Selection Guides which are published at:
<http://hpsweb.honeywell.com/Cultures/en-US/Products/Instrumentation/ProductModelSelectionGuides/default.htm>

Model Selection Guide

Honeywell

51-51-16U-78

Issue 13

Page 1 of 3

UDC1200 MICRO-PRO Universal Digital Controller

Model Selection Guide

Instructions

- Select the desired key number. The arrow to the right marks the selections available.
- Make one selection each from Tables I through VIII using the column below the proper arrow.

Key Number	I	II	III	IV	V	VI	VII	VIII
DC _ _ _ _	-	-	-	-	-	-	-	-

KEY NUMBER	Description	Selection	Availability
1/16 DIN Controller:	RTD or Linear mV	DC1201	↓
48x48mm	Thermocouple	DC1202	↓
Input Type	Linear mA	DC1203	↓
(Field Selectable)	Linear Voltage	DC1204	↓
	Limit Controller - FM Approved	DC120L	↓
	TPSC Controller (Thermocouple Factory Set)	DC120T	↓

TABLE I

Output 1	Relay	1	•	•	•	•	•	•
	SSR Driver	2	•	•	•	•	•	•
	Linear: 0 - 10 Volts	3	•	•	•	•	•	•
	Linear: 0 - 20 mA	4	•	•	•	•	•	•
	Linear: 0 - 5 Volts	5	•	•	•	•	•	•
	Linear: 4-20mA	7	•	•	•	•	•	•

TABLE II

Output 2	None	0	•	•	•	•	•	•
	Relay	1	•	•	•	•	•	•
	SSR Driver	2	•	•	•	•	•	•
	Linear: 0 - 10 Volts	3	•	•	•	•	•	•
	Linear: 0 - 20 ma	4	•	•	•	•	•	•
	Linear: 0 - 5 Volts	5	•	•	•	•	•	•
	Linear: 4-20mA	7	•	•	•	•	•	•
	Dual Relay Board	9						•

TABLE III

Output 3	None	0	•	•	•	•	•	•
	Relay	1	•	•	•	•	•	•
	SSR Driver	2	•	•	•	•	•	•
	Linear: 4-20mA	7	•	•	•	•	•	•
	Transmitter Power Supply (24Vdc)	8	•	•	•	•	•	•

TABLE IV

Communications	No Selection	0	•	•	•	•	•	•
	RS485 ASCII Serial Communication	1	•	•	•	•	•	•
	Digital Input (SP1/SP2 Selection or Auto/Manual Selection or DC100L Remote Reset)	2	•	•	•	•	•	•
	RS485 MODBUS Communication	3	•	•	•	•	•	•
	Basic Remote Setpoint	4	•	•	•	•	•	•

				Availability						
				DC120						
				Selection	1	2	3	4	L	T
TABLE V										
Power Supply	Power Supply 90 to 264 Vac			1	•	•	•	•	•	•
	Power Supply 24 to 48 Vac/dc			2	•	•	•	•	•	•
TABLE VI										
Manuals	English	(51-52-25-123)		0	•	•	•	•	•	•
(Single sheet	French	(51-52-25-123-FR)		1	•	•	•	•	•	•
Concise manuals	German	(51-52-25-123-GE)		2	•	•	•	•	•	•
for UDC1200)	Italian	(51-52-25-123-IT)		3	•	•	•	•	•	•
	Spanish	(51-52-25-123-SP)		4	•	•	•	•	•	•
TABLE VII										
Packaging	Individual Carton			0	•	•	•	•	•	•
	Bulk Pack of 10 identical models			1	•	•	•	•	•	•
	Bulk Pack of 50 identical models			2	•	•	•	•	•	•
	Bulk Pack of 100 identical models			3	•	•	•	•	•	•
TABLE VIII										
Specials	UDC1200 style overlay			0	•	•	•	•	•	•
	Special Instrument (Consult Factory)			S						

UDC1200 MICRO-PRO Universal Digital Controller

Supplemental Accessories & Kits

Description	Part Number
Option Slot 1	
Relay module	51453391-501
10 Vdc SSR Driver module	51453391-502
Linear (mA/Vdc) module	51453391-504
Option Slot 2 & 3	
Relay module	51453391-506
10 Vdc SSR Driver module	51453391-507
Linear (mA/Vdc) module	51453391-509
Dual Relay Board (Slot 2 only)	51453391-510
24Vdc transmitter module (Slot 3 only)	51453391-511
Option Slot A	
RS485 communication module	51453391-512
Digital Input module	51453391-513
Basic Remote Setpoint module	51453391-515
Others	
PC Software (includes the cable)	51453391-514
Product Manual (8 1/2 x 11)	English 51-52-25-122
	French 51-52-25-122-FR
UDC1000/1200 Fixing strap	46189016-501
UDC1500/1700 Fixing strap	46189017-501
UDC1000/1200 Replacement case	46189018-501
UDC1500/1700 Replacement case	46189019-501
DIN Rail Adaptor Kit	46189025-501

Model Selection Guides are subject to change and are inserted into the specifications as guidance only.
Prior to specifying or ordering a model check for the latest revision Model Selection Guides which are published at:
<http://hpsweb.honeywell.com/Cultures/en-US/Products/Instrumentation/ProductModelSelectionGuides/default.htm>

Model Selection Guide

Honeywell

51-51-16U-85

Issue 8

Page 1 of 3

UDC1700 MICRO-PRO Universal Digital Controller

Model Selection Guide

Instructions

- Select the desired key number. The arrow to the right marks the selections available.
- Make one selection each from Tables I through VIII using the column below the proper arrow.

Key Number	I	II	III	IV	V	VI	VII	VIII
_____ - _____ - _____ - _____ - _____ - _____ - _____ - _____ - _____								

KEY NUMBER	Description	Selection	Availability					
1/8 DIN Controller: 48x96mm	RTD or Linear mV	DC1701	↓					
Input Type (Field Selectable)	Thermocouple	DC1702	↓	↓				
	Linear mA	DC1703		↓				
	Linear Voltage	DC1704			↓			
	TPSC Controller *	DC170T				↓		
	Remote Setpoint, Fuzzy Logic, Digital Input *	DC170R					↓	
	* factory set for thermocouple input							

TABLE I

Output 1	Relay	1	•	•	•	•	•	•
	SSR Driver	2	•	•	•	•	•	•
	Linear 0 to 10 Volts	3	•	•	•	•	•	•
	Linear 0 to 20 ma	4	•	•	•	•	•	•
	Linear 0 to 5 Volts	5	•	•	•	•	•	•
	Linear 4 to 20 mA	7	•	•	•	•	•	•

TABLE II

Output 2	None	0	•	•	•	•	•	•
	Relay	1	•	•	•	•	•	•
	SSR Driver	2	•	•	•	•	•	•
	Linear 0 to 10 Volts	3	•	•	•	•	•	•
	Linear 0 to 20 ma	4	•	•	•	•	•	•
	Linear 0 to 5 Volts	5	•	•	•	•	•	•
	Linear 4 to 20 mA	7	•	•	•	•	•	•
	Dual Relay Board	9					•	

TABLE III

Output 3	None	0	•	•	•	•	•	•
	Relay	1	•	•	•	•	•	•
	SSR Driver	2	•	•	•	•	•	•
	Linear 0 to 10 Volts	3	•	•	•	•	•	•
	Linear 0 to 20 ma	4	•	•	•	•	•	•
	Linear 0 to 5 Volts	5	•	•	•	•	•	•
	Linear 4 to 20 mA	7	•	•	•	•	•	•
	Transmitter Power Supply (24Vdc)	8	•	•	•	•	•	•
	Dual Relay Board	9					•	

Model Selection Guide (continued)

				DC170	Availability					
					↓	↓	↓	↓	↓	↓
TABLE IV				Selection	1	2	3	4	T	R
Option 1		No Selection		0	•	•	•	•	•	•
		RS485 ASCII Serial Communication		1	•	•	•	•		•
		Digital Input (SP1/SP2 Selection)		2	•	•	•	•	•	•
		RS485 MODBUS Communication		3	•	•	•	•	•	•
		Basic Remote Setpoint		4	•	•	•	•	•	
TABLE V										
Option 2		Power Supply 90 to 264 Vac		1	•	•	•	•	•	•
		Power Supply 24 to 48 Vac/dc		2	•	•	•	•	•	•
TABLE VI										
Manuals (Single sheet Concise manuals for UDC1200)	English	(51-52-25-123)		0	•	•	•	•	•	•
	French	(51-52-25-123-FR)		1	•	•	•	•	•	•
	German	(51-52-25-123-GE)		2	•	•	•	•	•	•
	Italian	(51-52-25-123-IT)		3	•	•	•	•	•	•
	Spanish	(51-52-25-123-SP)		4	•	•	•	•	•	•
TABLE VII										
Packaging	Individual Carton			0	•	•	•	•	•	•
	Bulk Pack of 10 identical models			1	•	•	•	•	•	•
	Bulk Pack of 50 identical models			2	•	•	•	•	•	•
TABLE VIII										
Special	None			0	•	•	•	•	•	•
	Special Instrument (Consult Factory)			S						

UDC1700 MICRO-PRO						Supplemental					
Universal Digital Controller						Accessories & Kits					
Description								Part Number			
Option Slot 1											
Relay module								51453391-501			
10 Vdc SSR Driver module								51453391-502			
Linear (mA/Vdc) module								51453391-504			
Option Slot 2 & 3											
Relay module								51453391-506			
10 Vdc SSR Driver module								51453391-507			
Linear (mA/Vdc) module								51453391-509			
Dual Relay Board								51453391-510			
24Vdc transmitter module (Slot 3 only)								51453391-511			
Option Slot A											
RS485 communication module								51453391-512			
Digital Input module								51453391-513			
Basic Remote Setpoint module								51453391-515			
Option Slot B											
Full remote Setpoint module (to upgrade a DC1700 to a DC170R)								51453391-516			
Others											
PC Software (includes the cable)								51453391-514			
Product Manual (8 1/2 x 11)						English		51-52-25-122			
						French		51-52-25-122-FR			
UDC1000/1200 Fixing strap								46189016-501			
UDC1500/1700 Fixing strap								46189017-501			
UDC1000/1200 Replacement case								46189018-501			
UDC1500/1700 Replacement case								46189019-501			
DIN Rail Adaptor Kit								46189025-501			

Warranty/Remedy

Honeywell warrants goods of its manufacture as being free of defective materials and faulty workmanship. Contact your local sales office for warranty information. If warranted goods are returned to Honeywell during the period of coverage, Honeywell will repair or replace without charge those items it finds defective. The foregoing is Buyer's sole remedy and is **in lieu of all other warranties, expressed or implied, including those of merchantability and fitness for a particular purpose.** Specifications may change without notice. The information we supply is believed to be accurate and reliable as of this printing. However, we assume no responsibility for its use.

While we provide application assistance personally, through our literature and the Honeywell web site, it is up to the customer to determine the suitability of the product in the application.

Specifications are subject to change without notice.

For More Information

Learn more about how Honeywell's UDC1200/1700 Micro-Pro Series can monitor and control temperatures, pressures and levels in a wide range of applications visit our website www.honeywell.com/ps/hfs or contact your Honeywell account manager.

Honeywell Process Solutions

1860 W. Rose Garden Lane
Phoenix, Arizona 85027
Tel: 1-800-423-9883 or 1-800-343-0228
www.honeywell.com/ps

51-52-03-35
June 2011
© 2011 Honeywell International Inc.

The Honeywell logo, consisting of the word "Honeywell" in a bold, red, sans-serif font.